

# USB 3.0 1-Port PCI Express Card

## User Manual

### Features

- Fully compliant with PCI Express Base Specification Revision 2.0
- Single-lane (x1) PCI Express throughput rates up to 5 Gbps
- Compliant with Universal Serial Bus 3.0 specification Revision 1.0
- Supports simultaneous operation of multiple USB 3.0, USB 2.0 and USB 1.1 devices
- Supports the following speed data rates as follows:
- Low-speed (1.5Mbps) / Full-speed (12Mbps) / High-speed (480Mbps) / Super-speed (5Gbps)
- Compliant with Intel's eXtensible Host Controller Interface (xHCI) Specification 0.96
- Supports 1 downstream ports for all speeds
- Hot-swapping feature allows you to connect/disconnect devices
- without powering down the system
- Support Windows XP/Vista/7 (32/64 bit)

### System Requirements

- Windows XP/Vista/7 (32/64 bit)
- One available PCI Express slot (Recommend PCI Express 2.0)

### Package Contents

- 1 x USB 3.0 1-Port PCI Express Card
- 1 x Driver CD
- 1 x User Manual

*Note: Contents may vary depending on country/market.*

### Hardware Installation

1. Turn off the power to your computer.
2. Unplug the power cord and remove your computer's cover.
3. Remove the slot bracket from an available PCIe slot.

4. To install the card, carefully align the card's bus connector with the selected PCIe slot on the motherboard. Push the board down firmly.
5. Replace the slot bracket's holding screw to secure the card.
6. Replace the computer cover and reconnect the power cord.

### Driver Installation

For Windows XP/Vista/7 (32/64 bit)

1. Please insert the CD driver bound with USB 3.0 1-Port PCI Express Card into your CD-ROM Drive
2. At the Windows desktop, click Start, Run.
3. Type D:\Fresco Logic\WHQL Driver 32bit\W7xp.msi(Windows7/XP\_32bit)  
D:\Fresco Logic\WHQL Driver 32bit\Vista.msi(Windows Vista\_32bit)  
D:\Fresco Logic\WHQL Driver 64bit\W7XP\_64bit.msi(Windows7/XP\_64bit)  
D:\Fresco Logic\WHQL Driver 64bit\Vista\_64bit.msi(Windows Vista\_64bit)  
click OK. (Change D: to match your CD-ROM drive letter)
4. Follow the on-screen instructions to complete the installation.

All brand names and trademarks are properties of their respective owners